

marantz®



SR5013

7.2 CHANNEL AV RECEIVER WITH HEOS MUSIC STREAMING

The Marantz SR5013 7.2 channel AV receiver offers immersive home theater and high-resolution audio support. Enjoy multi-dimensional surround sound with the latest audio formats in Dolby Atmos, DTS:X and DTS Virtual:X. The SR5013 is fully compatible with the latest HDMI specifications, including 4K video, and lets you stream wireless music from your smart devices via Bluetooth, AirPlay or the HEOS app.

Highlights

- 7.2 channel discrete power amplifier, 100W per channel (8-ohm, 20Hz – 20kHz, 0.08% THD)
- 8 HDMI inputs — including one HDMI input on the front panel — with full HDCP 2.2 support, plus two HDMI outputs
- 4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR and BT.2020, plus Dolby Vision compatibility and Hybrid Log-Gamma (HLG)
- Supports object-based audio formats Dolby Atmos, DTS:X and DTS Virtual:X processing
- Ability to decode high-resolution audio ALAC, FLAC and WAV lossless files up to 24-bit/192-kHz — plus DSD 2.8MHz and 5.6MHz tracks let you enjoy music exactly as the artist intended
- Marantz proprietary HDAM circuit boards for more detailed, dynamic sound
- Built-in HEOS wireless multi-room audio technology
- Amazon Alexa voice control via the HEOS Home Entertainment skill
- Stream the most popular music services — like Spotify, Pandora, Tunes, Deezer and many others — via Bluetooth, AirPlay 2 or the HEOS app
- Integrated Phono input to connect to your turntable
- Optimize your audio experience with Audyssey MultEQ, Dynamic Volume and Dynamic EQ for a seamless setup within your listening environment
- Setup assistant, advanced GUI and Marantz 2016 AVR remote app for an easy out-of-box experience
- Built-in Wi-Fi with 2.4GHz/5GHz dual band support (dual antenna)



because music matters

SR5013

7.2 CHANNEL AV RECEIVER WITH HEOS MUSIC STREAMING



Design and specifications are subject to change by Marantz without notice.

| FEATURES | SR5013 |
|---|--------------------------------|
| MULTICHANNEL SURROUND | |
| DTS HD Master / DTS:X / DTS Neural:X | • / • / • |
| DTS Virtual:X | • |
| Dolby TrueHD / Dolby Atmos / Dolby Surround | • / • / • |
| Auro-3D / Auromatic | - / - |
| Multichannel stereo | • |
| Max number of processing (Preamp) channels | 7.1 |
| Audyssey | MultEQ XT |
| Audyssey Dynamic EQ / Dynamic Volume | • / • |
| Compressed audio enhancer: MDAX2 | • |
| NETWORK | |
| HEOS Multi-room streaming / network audio streaming | • / • |
| Lossy formats: MP3 / WMA / AAC | • / • / • |
| Lossless formats: FLAC / ALAC / WAV | • / • / • |
| FLAC HD 192/24 / WAV 192/24 / ALAC 192/24 | • / • / • |
| DSD audio streaming | up to DSD5.6 |
| Gapless playback | • (FLAC, WAV, ALAC, DSD) |
| AirPlay audio streaming | • (AirPlay2 via FW update) |
| Internet Radio (Tuneln) | • (Tuneln) |
| Spotify connect / Deezer / TIDAL / Napster / Pandora / SiriusXM | • / • / • / • / • / • |
| Compatible with Remote app (iOS/Android) | Marantz 2016 AVR Remote |
| Ethernet / Wi-Fi | • / • (dual antenna/dual band) |
| Bluetooth | • |
| HDMI | |
| 4K 60Hz 4:4:4 resolution / HDCP 2.2 | • / • |
| eARC (Enhanced Audio Return Channel) | - |
| Analog to HDMI scaling | 480i/576i up to 4K 30/25/24 |
| HDMI to HDMI scaling | up to 4K 30/25/24 |
| GUI overlay on HDMI | • |
| HDR / HLG / Dolby Vision | • (HDR10) / • / • |
| 3D signal pass-through | • |
| HDMI pass-through in Standby Mode | • |

| | | |
|---|--------------------|--------------|
| MULTIROOM / CI | | |
| HEOS multi-room integrated | • | |
| HEOS Link compatibility: IR/ IP | • / • | |
| Multi-room zones | 2 | |
| Zone audio source: HDMI / Opt, Coax / Network, USB / Analog | - / - / • / • | |
| IP Control / RS232 Control / Web Control / App Control | • / • / • / • | |
| Domotz Pro / IHIJI | • / • | |
| INPUTS/OUTPUTS | | |
| VIDEO | | |
| Composite in/out | 2+1 / 1 | |
| Component in/out | 2 / 1 | |
| HDMI in/out | 7+1 / 2 | |
| AUDIO | | |
| Analog In / Out | 4+1 / - | |
| Phono (MM) in | • | |
| Digital in: Optical / Coaxial | 2 / 2 | |
| Multi-room out: Analog / Digital | 1 / - | |
| Multichannel pre-out | • (7.2) | |
| Subwoofer out | 2 | |
| 7.1 Multichannel input | • | |
| OTHER | | |
| Speaker terminal: gold plated screw / regular screw | - / • | |
| SPECIFICATIONS | | |
| Number of poweramps | 7 | |
| Number of speaker terminals | 7 | |
| Power output (8 ohm, 20 Hz - 20 kHz, 0.08% 2ch drive) | 100 W | |
| Power output (8 ohm, 20 Hz - 20 kHz, 0.05% 2ch drive) | - | |
| Power output (6 ohm, 1 kHz, 10% 1ch drive) | 200 W | |
| GENERAL | | |
| System remote control | RC035SR | |
| Power consumption in W | 650 | |
| Power consumption no-sound (ECO on / off) in W | 45 W / 75 W | |
| Standby consumption in W | 0.2 (with CEC 0.5) | |
| Maximum dimensions w/o antenna: (W x D x H) in mm | 17.3 x 13.3 x 6.3 | |
| Weight in lbs | 22.1 | |
| UPC | | |
| SR5013/U1B | Black | 699927201654 |

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

* All specs can be subject to change.